

# **DH-Robotics Technology Co.,Ltd.**





EN-3.3.2024.10 en.dh-robotics.com

info@dh-robotics.com

14th Floor, Building A4, Nanshan Intelligence Park, No. 1001 Xueyuan Avenue, Taoyuan Street, Nanshan District, Shenzhen City, Guangdong Province, China



# **DH-ROBOTICS**

# LINEAR COIL **ACTUATOR**



# CONTENTS

Introduction To Linear Coil Actuator	02
VLA Series Linear Coil Actuator	09
VLAR Series Linear Rotary Coil Actuator	23
DLAR Series Direct Drive Linear Rotary Actuator	33
DLSR Series Direct Drive Linear Rotary Actuator	45
DLE Series Direct Drive Linear Module	49
Linear Coil Actuator Drive	55


# **FEATURES AND APPLICATIONS**

Product Series	Drive Mode	Maximum Stroke	Maximum Thrust	Application Scenarios
VLA	Linear		30N	<b>3C testing industry:</b> key testing of mobile phones and computers, panel testing, and watch strap testing.
	Coil Motor	25mm		<b>Automotive industry:</b> key and switch testing of automotive centre stack.
<b>T</b>				<b>Semiconductor industry:</b> chip testing, chip sorting, etc.
VLAR	Linear Coil	25mm	16N	<b>Semiconductor industry:</b> IGBT chip bonding, chip sorting, testing, etc.
	Motor + Servo Motor			<b>3C industry:</b> precision parts assembly, mobile phone cameras assembly, force controlled stud implantation, automatic transplanting, loading and unloading, accessories mounting, etc.
DLAR	DLAR Linear Motor + 50mm Servo Motor			<b>Semiconductor industry:</b> IGBT chip bonding, chip sorting, testing, etc.
		60N	<b>3C industry:</b> Precision parts assembly, mobile phone cameras assembly, force controlled stub implantation, force controlled BTB snap-fit, automatic transplanting, loading and unloading, accessories mounting, etc.	
DLSR	Linear Motor + Closed-loop Stepper Motor	50mm	26N	<b>3C industry:</b> precision parts assembly, force controlled stud implantation, automatic transplanting, loading and unloading, accessories mounting, PCB board plug-in, flexible circuit board mounting and reinforcing, etc.
				Renewable energy: loading and unloading of small battery parts.
DLE	Linear Motor	50mm	54N	<b>3C industry:</b> precision parts assembly, line scanning detection, force controlled push and positioning, terminal snap-fit, automatic transplanting, loading and unloading, etc.

Note: These are the product features and applications of standard Linear coil actuator products (excluding customized products) of DH-Robotics.


## **PRODUCT FEATURES**

Compact design, thin and light. The thinnest product thickness is only 10 mm



#### **Soft Landing**

Contact the surface of an object with high speed and low force



3 Working Modes

- Velocity mode
- Torque mode
- Position mode







Precision



Automated production line

**Scenarios** 



Hi-speed pick and place



machining





- Stroke resolution: up to 0.5 μm
- Positioning repeatability: ±2 μm
- Rotary position resolution: 0.005°

The force generated by the voice coil actuator is proportional to the current. The voice coil actuator is combined with a high-performance guide rail. The coil and stator parts of the motor are non-contact and wear-free, and the force control accuracy of up to  $\pm 5$  g can be achieved.

High-precision magnetic encoder with micron-level resolution. Optical encoder with 0.1µm resolution, Magnetic grid encoder with 1µm resolution.

The DH-Robotics voice coil actuator is a direct drive motor combined with a micron-level magnetic encoder. When it positions to the same point repeatedly, the accuracy deviation of the stop position is  $\pm 2 \,\mu m$ .

The DH-Robotics voice coil actuator is designed to be highly integrated, with a minimum thickness of 10 mm for the series of products, greatly saving the internal space of the module device and facilitating the arrangement of the multi-motor matrix combination.

The intelligent soft landing function enables the target object to be softly touched with precise force control. This technology reduces the scratch rate and fragmentation rate of precision fragile or high unit price parts. In this way, the yield rate and productivity are improved.

# **PRODUCT ADVANTAGES**

±5 g **Force Control Accuracy** 

0.5 μm **Stroke** Resolution

 $\pm 2 \mu m$ **Positioning** Repeatability

**10 mm Optimal Thickness** 

Soft Landing

www.dh-robotics.com 3/4

## **ADVANTAGES OVER CONVENTIONAL SOLUTION**

#### Take chip packaging as an example:

#### **Pain Points**

The conventional chip pickup mechanism contacts the chip too fast, and the contact force is too large, which will cause the chip to be damaged due to excessive pressing. And it cannot achieve high force control, limiting the efficiency of the chip mounting process.

	Conventional Solution	DH-Robotics Solution
Device used	Combined mounting head	VLAR-20-25 voice coil linear rotary actuator
Motion module	The module is integrated with: Linear motor Servo motor/stepper motor Voice coil motor (VCM)	All-in-one integrated module design
Repeatability	Positioning repeatability: $\pm 10~\mu m$ Rotation repeatability: $\pm 0.5~^\circ$ Force control accuracy: $\pm 10~g$	Positioning repeatability: ±2 µm ↑ Improved by more than 5 times Rotation repeatability: ±0.02° ↑ Improved by more than 10 times Force control accuracy: ±5 g ↑ Improved by more than 2 times

The advantages of DH-Robotics voice coil actuator compared with the common combined mounting head are:



**Integrated Design Small Volume Saving Device Space** 




**Higher Accuracy Faster More Stable Motion** 




**Precision Component Less Wear Longer Service Life** 

## **APPLICATIONS**




#### Flexible Pick and Place of **Vulnerable Components**

The voice coil actuator can provide accurate linear and rotary motions of the Z-axis while performing high-speed pick-and-place motions. With the soft landing function, it can touch precision components with a force of  $\pm 5$  g to protect the components from damage, for example, in chip packaging and camera module assembly.




#### **Electronics Testing**

Highly integrated design, the minimum thickness can reach 10mm, suitable for multi-motor matrix combination arrangement, and can complete a variety of touch operation modes. The force control accuracy is  $\pm 5g$ , the repeat accuracy (position) is  $\pm 2\mu m$ , the product runs stably, so that the detection efficiency is improved. It can be applied to touch panel testing, keyboard testing, switch testing.



#### **New Energy Battery Thickness** Measurement

The thrust and speed of the actuator are set through the program, and the battery pack is pushed flexibly. When the set force is reached, the position is measured and the thickness information of the battery pack is output. The characteristics of high stability, high frequency and long life of the voice coil actuator can ensure long-term, efficient, accurate and stable execution of detection.



#### **High-precision Parts Assembly**

Miniature electronic components have high require ments for production and assembly, such as camera module assembly. The precise force control and soft landing capability of the voice coil linear rotary actuator can prevent parts from being damaged; high position repeatability ensures the accuracy of positioning and assembly and improves the overall assembly production yield.

# Q&A

#### Q: How to quickly select a right Linear coil actuator?

A: Please select the Linear coil actuator according to the "Voice Coil Selection Procedure".

#### O:What is the impact of different installation methods of a Linear coil actuator on its use?

A: Vertical installation with the vertical rod pointing down: In general usage scenarios, use the product as recommended. The product performance will not be affected. Horizontal or vertical installation with the vertical rod pointing up: in unconventional usage scenarios, there may be insufficient motor output. You are advised to remove the internal spring to reduce the load weight before use.

#### Q:What is the relationship between resolution, repeatability, and absolute positioning accuracy?

A: Resolution: refers to the smallest amount of change that the system can detect, that is, the minimum movement distance or minimum rotation angle that each axis of the system can achieve. The resolution directly affects the fine control ability of the system. A high resolution means that the system can more accurately control the motion to a smaller unit.

Positioning repeatability: refers to the consistency and stability that the system can maintain when the same action is repeated several times under the same conditions. The positioning repeatability determines the reliability of the system in dynamic or repeatable actions. A high positioning repeatability means that the system can maintain consistent performance when performing the same action for many times.

Absolute positioning accuracy: refers to how close the actual position of the system is to the ideal target position. This parameter reflects the positioning ability of the system under static conditions. The increase of positioning accuracy usually depends on the mechanical accuracy, electrical accuracy, and the optimization of control algorithm.

Increased resolution can directly improve positioning accuracy, as a higher resolution means the system can more accurately identify and control motion to a smaller unit. However, resolution may not be directly related to positioning accuracy, as the actual positioning accuracy is also affected by mechanical errors, electrical errors, and control algorithms. The positioning repeatability is related to the mechanical structure of the system, the error of the transmission system, the rigidity of the structure, and other factors, which will affect the repeatability of the system.

#### Q:What is soft landing?


A: In velocity mode, the Linear coil motor controls the robot to approach the surface of an object at low force while continuously monitoring the position error. Once the robot contacts the surface of the object, the motor actuator shaft will remain in the position on the surface of the object when the position error increases to the pre-set value. The purpose of soft landing is to control force properly when the actuator contacts the machining part to prevent device damage or other pressure-induced problems.

#### Q: What is the force control accuracy of DH-Robotics Linear coil actuator and what factors are related to it?

A: The force control accuracy depends on product specifications. Under the rated load, the open-loop force control accuracy of a conventional linear/rotary actuator is within  $\pm$  10 g and can be up to  $\pm$  3 g, and the closed-loop force control accuracy is within  $\pm$ 1 g. The force control accuracy is mainly related to actuator type, load size, running tempo, and controller performance. Generally speaking, the higher the load, the higher the running tempo, the higher the control difficulty, the lower the force control accuracy. A voice coil is superior to A linear motor, and the higher the controller performance, the higher the force control accuracy.

#### Q: How does a Linear coil actuator calculate the output according to the cycle time?

A: The output can be calculated according to the following motion plan and formula. For more information, consult the DH-Robotics technical support.



#### Q:What is the difference between the VLAR series and the DLAR series?

A:These two series are linear/rotary actuators. The VLAR series is driven by a voice coil while the DLAR series is driven by a linear motor. The VLAR series features short stroke, small size, and light weight, while the DLAR series features both short and long stroke and larger size and weight.

#### Q: How long is the control cable?

A:As standard configurations, cable length options of DH-robotics Linear coil actuator include 3 m, 5 m, 7 m, and 10 m.

#### Q:Which control modes are supported for Linear coil actuator?

A:The commonly used control modes on the market are supported, such as EtherCAT, Modbus, Canopen and pulse control. However, translation gateways are required for Profinet and CC-Link.


#### Q: How much radial force can the vertical rod of the actuator withstand?

A:The Linear coil actuator is a precision device and the output end is a high-precision shaft. Therefore, try your best to avoid hard collision in the radial direction. The linear actuator can operates normally under a certain degree of sliding lateral force, and the lateral force is recommended to be less than 2 N. The linear/rotary actuator features a complex internal structure. Do not subject it to lateral force.

#### Q:What is the diameter of the control cable?What are the wiring requirements?

A: The control cable is approximately 8 mm in diameter. For wiring requirements, refer to Cable Installation Requirements of Voice Coil Actuators of DH-Robotics.

# **SELECTION PROCEDURE**



www.dh-robotics.com 7/8

# **VLA SERIES Linear Coil Actuator**

VLA-10-20 (Vacuum)


**VLA-16-15** 

VLA-16-15 (Vacuum)

VLA-25-10 (Vacuum)

VLA-25-25

VLA-30-25



## **PRODUCT FEATURES**

# High Force Repeatability Soft Landing

The thrust repeatability of VLA series of products is within  $\pm 5$  g, meeting the production and assembly requirements of semiconductors, optoelectronics, and other industries for high force control accuracy.

#### Light, Thin, and Easy to use Adjustable Parameters

The product design is compact, light and thin, and has strong maneuverability. You can adjust the speed, thrust, and position parameters and set different modes through the control software.

#### **High-speed and High** Frequency Long life over 100 Million Cycles


With high response-ability, high speed, and high frequen cy, the frequency can reach more than 30 Hz without load. The service life is up to 100 million cycles, and it is stable and durable.

## **INSTALLATION METHOD**


Install it using the screw holes on the back of the product

#### **Installation Directions:**

- Horizontal direction
- Vertical installation with the vertical rod pointing down
- Vertical installation with the vertical rod pointing up








# **APPLICATION SCENARIOS**


The force repeatability of  $\pm 5$  g, micron-level resolution, and ultra-high motion frequency of the VLA series help to improve the efficiency and yield rate of quick pick-and-place, assembly, testing, and other scenarios in semiconduc tor, 3C electronics, optoelectronics, and other industries.



# VLA-10-20 (Vacuum)


**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**



#### \*Note: For customization fees, consult the company's sales staff


# **TECHNICAL SPECIFICATIONS**











#### **Performance Specifications**

Peak thrust

Continuous thrus	st* <sup>®</sup> 1.8 N	
Calculation formula for line motor output (vertically do	rar shaft F=2.15-0	.027*L (For the actual output, reference the thrust-displacement cu
Total stroke	20 mm	

Force control accuracy\*3  $30 \, \text{g} \sim 100 \, \text{g} : \pm 5 \, \text{g}$ 

1.8 N/A Force constant

Linear encoder resolution 1 µm (Magnetic encoder)

Linear positioning repeatability ±5 µm

#### **Mechanical Specifications**

Overall mass	130 g
Movable part mass	30 g

85 mm x 58 mm x 10 mm

Recommended air pressure range<sup>★®</sup> -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Operating voltage  $24 \text{ V DC} \pm 10\%$ 

1.0 A Continuous current Peak current 2.2 A Recommended load  $< 30 \, \mathrm{g}$ 

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating


Recommended operating 0~40°C, 85% RH or less environment

International standard compliance CE, FCC, RoHS

There is an error of  $\pm$  0.3 N between the the

DH-Robotics technical support \*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers






# VLA-16-15


**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**



#### \*Note: For customization fees, consult the company's sales staff


# **TECHNICAL SPECIFICATIONS**











#### **Performance Specifications**

Peak thrust	6 N	
Continuous thrust*®	3 N	

Calculation formula for linear shaf motor output (vertically down)\*2 F=2.60-0.032\*L (For the actual output, refer to the thrust-displacement curve) 15 mm Total stroke

Force control accuracy\*3  $30 \, \text{g} \sim 200 \, \text{g} : \pm 5 \, \text{g}$ 

3 N/A Force constant

Linear encoder resolution 1 µm(Magnetic encoder)

Linear positioning repeatability ±5 µm

#### **Mechanical Specifications**

Overall mass Movable part mass 30 g

80 mm x 55 mm x 16 mm

Recommended air pressure range\*

Without vacuum

#### **Operating Environment**

Operating voltage 24 V DC  $\pm 10\%$ 

1.0 A Continuous current Peak current 2.0 A Recommended load  $< 80 \, \mathrm{g}$ 

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating


Recommended operating environment 0~40°C, 85% RH or less

International standard compliance

CE, FCC, RoHS

3 There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition for the output calculation of other installation methods, please consult DH-Robotics engineers; related to the load size, running tempo, etc. If you need a higher accuracy, please consult the


DH-Robotics technical support \*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers




# VLA-16-15 (Vacuum)

**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











#### **Performance Specifications**

reak tillust	OIN
Continuous thrust*®	3 N
Calculation formula for linear shaft	F-2 15-0 027*I (For the actua

F=2.15-0.027\*L the thrust-displacement curve) motor output (vertically down)\*2 15 mm Total stroke

Force control accuracy\*®  $30 \, \text{g} \sim 200 \, \text{g} : \pm 5 \, \text{g}$ 

3 N/A Force constant

Linear encoder resolution 1 µm(Magnetic encoder)

Linear positioning repeatability ±5 μm

#### **Mechanical Specifications**

Overall mass	220 g
Movable part mass	30 g

100 mm x 62 mm x 16 mm

Recommended air pressure range<sup>★</sup>
-0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Continuous current 1.0 A Peak current 2.0 A Recommended load  $< 80 \, \mathrm{g}$ 

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C, 85% RH or less environment


International standard


CE, FCC, RoHS compliance

There is an error of  $\pm$  0.3 N between the the

elated to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support

\*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers







# VLA-25-10 (Vacuum)

**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**














#### **Performance Specifications**

Continuous thrust*®	4.8 N
Calculation formula for linear shaft motor output (vertically down)*(2)	F=4.67-0.08*L (For the actual output, refer to the thrust-displacement curve)

10 mm Total stroke

 $30 g \sim 100 g$ :  $\pm 5 g$ Force control accuracy\*  $100 \, \text{g} \sim 400 \, \text{g} : \pm 5\%$ 

Force constant

Peak thrust

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass	310 g
Movable part mass	57 g

80 mm x 60 mm x 25 mm

Recommended air pressure range<sup>★</sup> • -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Operating voltage	24 V DC ±10%
Continuous current	0.7 A
Peak current	1.8 A
Recommended load	< 80 g
Maintenance interval	Refer to Maintenance Instructions for DH-Robotics Linear coil actuator

Recommended operating 0~40°C, 85% RH or less environment

International standard


There is an error of  $\pm 0.3$  N between the theoretical calculation formula and the actual condition


For the output calculation of other installation methods, please consult DH-Robotics engineers:

(3) It is the reference value under the recommended load. The actual force control accuracy is

DH-Robotics technical support

\*4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers.






# VLA-25-25


**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**



#### \*Note: For customization fees, consult the company's sales staff


# **TECHNICAL SPECIFICATIONS**











Performance Specif	ications
Peak thrust	11 N
Continuous thrust*®	6 N
Calculation formula for linear shaft motor output (vertically down)*②	F=6.68-0.018*L (For the actual output, refer to the thrust-displacement curve)
Total stroke	25 mm
Force control accuracy*®	$100 \text{ g} \sim 500 \text{ g}$ : $\pm 5 \text{ g}$
Force constant	5 N/A
Linear encoder resolution	1 μm(Magnetic encoder)
Linear positioning repeatability	±5 μm
Machanias I Currifia	-41

#### **Mechanical Specifications** 510 g Overall mass

Movable part mass 54 g

120 mm x 60 mm x 25 mm

Recommended air pressure range\*

Without vacuum

#### **Operating Environment**

Operating voltage  $24 \text{ V DC} \pm 10\%$ 1.2 A Continuous current

Peak current 2.2 A Recommended load < 150 g

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C, 85% RH or less environment

International standard compliance


CE, FCC, RoHS


 $\hat{D}$  Motor output without protective spring;  $\hat{D}$  There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition

or the output calculation of other installation methods, please consult DH-Robotics engineers:

It is the reference value under the recommended load. The actual force control accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the

\*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers.







# VLA-30-25

**LINEAR COIL ACTUATOR** 

# **SELECTION METHOD**




# TECHNICAL SPECIFICATIONS











#### **Performance Specifications**

Continuous thrust\*® 12 N (24 V) 16 N (48 V)

Calculation formula for linear shaft motor output (vertically down)\*® F=12.67-0.044\*L (For the actual output, refer to the thrust-displacement curve)

24 N (24 V)

30 N (48 V)

Total stroke 25mm

Peak thrust

Force control accuracy\*3 30 g~100 g:  $\pm 5$  g 100 g~800 g:  $\pm 5\%$ 

Force constant 8 N/A

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder)

± 2 µm (Optical encoder) ± 5 µm (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass 860 g Movable part mass 130 g

Size 140 mm x 75 mm x 30 mm

Recommended air pressure range\*

Without vacuum

#### **Operating Environment**

Operating voltage  $24 \text{ V DC} \pm 10 \%$ 

Continuous current 1.5 A (24 V) 2.0 A (48 V)
Peak current 3.0 A (24 V) 4.0 A (48 V)

Recommended load < 250 g

Maintenance interval Refer to Maintenance Instructions for DH-Robotics Linear coil actuator

IP rating IP 40

Recommended operating 0~40°C, 85% RH or less

International standard CE, FCC, RoHS

npliance CE, FCC, F


) Motor output without protective spring; ) There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual conditio


For the output calculation of other installation methods, please consult DH-Robotics engineers;


\*3) It is the reference value under the recommended load. The actual force control accuracy is

related to the load size, running tempo, etc. If you need a higher accuracy, please consult the

\*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers








# **VLAR SERIES Linear Rotary Coil Actuator**

**VLAR-20-15** 

**VLAR-20-25** 

**VLAR-25-25** 

**VLAR-25-40** 



## **PRODUCT FEATURES**

#### **High Performance Linear/Rotary Motion Adjustable Parameters**

#### Provide accurate linear and rotary actions of the Z-axis during high-speed motion, with adjustable velocity, thrust, and position parameters, enabling complex actions requiring high frequency

#### **Hollow Rod Soft Landing Power-off Protection**

The product is compact, light, and thin. It employs a hollow rod design to support pick-and-place tasks. The intelligent soft landing function protects the picked and placed workpiece with precise force control. The Z-axis has a built-in spring to prevent the axis from falling off due to power-off during vertical operations.

#### **Precision Resolution Long Life over** 100 Million Cycles

Regarding this product, the stroke resolution is up to 0.5 µm, the rotary position resolution is 0.005°, and the thrust repeatabil ity is within ±10 g. With high-quality guide rail-level related components, it has a service life of up to 100 million cycles, and it is stable and durable.

## **INSTALLATION METHOD**


Install it using the screw holes on the back of the product.

#### **Installation Directions:**


Horizontal direction

and high precision.

- Vertical installation with the vertical rod pointing down
- Vertical installation with the vertical rod pointing up







## **APPLICATION SCENARIOS**

The force repeatability of  $\pm 10$  g and the micron-level resolution can be applied to the fast pick-and-place, assembly, testing, and other scenarios in semiconductors, 3C electronics, and other industries.


The unique linear and rotary motions of the Z-axis of the VLAR series can adapt to more abundant industrial scenarios, such as positioning, correction, and assembly in medical automation, 3C, and packaging automation.




# VLAR-20-15

**LINEAR ROTARY COIL ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- \*② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult DH-Robotics engineers;
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;

  \*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers.

#### **Performance Specifications** Peak thrust

Continuous thrust\*® 8 N Calculation formula for linear shaft motor output (vertically down)\*② F=7.17-0.089\*L (For the actual output, refer to the thrust-displacement curve)

Total stroke

 $50 \,\mathrm{g} \sim 200 \,\mathrm{g} \colon \pm 10 \,\mathrm{g}$ Force control accuracy\*3  $200 \text{ g} \sim 600 \text{ g}: \pm 5\%$ 

0.04 N.M Maximum torque 0.01 N.M Rated torque

Force constant

Maximum speed 2000 RPM Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder)

6.7 N/A

Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Rotary positioning repeatability ±0.02° (Optical encoder) ±0.1° (Magnetic encoder)

#### **Mechanical Specifications**

610 g Overall mass Movable part mass 176 g

155 mm x 83 mm x 20 mm

Recommended air pressure range<sup>★</sup> -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

24 V DC ±10% Operating voltage (Linear) 1.2 A (Rotary) 0.6 A Continuous current

Peak current (Linear) 2.5 A (Rotary) 2.5 A < 100 g

Recommended load inertia 10 g.cm<sup>2</sup>


Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended load

Recommended operating 0~40°C. 85% RH or less


International standard compliance CE. FCC. RoHS




# VLAR-20-25

**LINEAR ROTARY COIL ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- 4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust

Continuous thrust\*® 8 N Calculation formula for linear shaft motor output (vertically down)\*② F=7.77-0.089\*L (For the actual output, refer to the thrust-displacement curve)

Total stroke 25 mm

 $50 \, \text{g} \sim 200 \, \text{g}$ :  $\pm 10 \, \text{g}$ Force control accuracy\*3  $200 \text{ g} \sim 600 \text{ g}: \pm 5\%$ 

6.7 N/A Force constant 0.056 N.M Maximum torque

0.014 N.M Rated torque Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Rotary positioning repeatability ±0.02° (Optical encoder) ±0.1° (Magnetic encoder)

#### **Mechanical Specifications**

720 g Overall mass Movable part mass

170 mm x 83 mm x 20 mm

Recommended air pressure range\* -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

24 V DC ±10% Operating voltage (Linear) 1.2 A (Rotary) 0.6 A Continuous current

(Linear) 2.5 A (Rotary) 2.5 A Peak current Recommended load

Recommended load inertia 10 g.cm<sup>2</sup>


Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C, 85% RH or less environment

International standard compliance


CE, FCC, RoHS




# VLAR-25-25

**LINEAR ROTARY COIL ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult DH-Robotics engineers;
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- 4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust Continuous thrust\*® 8 N

Calculation formula for linear shaft motor output (vertically down)\*② F=9.384-0.10\*L (For the actual output, refer to the thrust-displacement curve) Total stroke

 $50 \, \text{g} \sim 200 \, \text{g} : \pm 10 \, \text{g}$ Force control accuracy\*3 200 g ~ 600g: ±5%

Force constant 6.7 N/A 0.072 N.M Maximum torque 0.025 N.M Rated torque

Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Rotary positioning repeatability ±0.02° (Optical encoder) ±0.1° (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass 1080 g Movable part mass

195 mm x 106 mm x 20 mm

Recommended air pressure range\*

(4) -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

24 V DC ±10% Operating voltage (Linear) 1.2 A (Rotary) 1 A Continuous current (Linear) 2.2 A (Rotary) 2.5 A Peak current Recommended load < 150 g

Recommended load inertia 70 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating


Recommended operating 0~40°C, 85% RH or less environment

CE, FCC, RoHS

International standard compliance








# VLAR-25-40

**LINEAR ROTARY COIL ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- 4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust

Continuous thrust\*® Calculation formula for linear shaft motor output (vertically down)\*② F=4.16-0.065\*L (For the actual output, refer to the thrust-displacement curve)

Total stroke 40 mm

 $50 \, \text{g} \sim 200 \, \text{g}$ :  $\pm 10 \, \text{g}$ Force control accuracy\*3  $200 \text{ g} \sim 400 \text{ g}: \pm 5\%$ 

4.6 N/A Force constant 0.056 N.M Maximum torque

Rated torque Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Rotary positioning repeatability ±0.02° (Optical encoder) ±0.1° (Magnetic encoder)

0.02 N.M

#### **Mechanical Specifications**

Overall mass 1130 g Movable part mass

195 mm x 106 mm x 20 mm

Recommended air pressure range\* -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

24 V DC ±10% Operating voltage

(Linear) 1.2 A (Rotary) 1.0 A Continuous current (Linear) 2.2 A (Rotary) 2.8 A Peak current

Recommended load  $< 100 \, \mathrm{g}$ 


Recommended load inertia 10 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C, 85% RH or less

environment International standard compliance CE, FCC, RoHS



# **DLAR SERIES Direct Drive Linear Rotary Actuator**

DI AR-16-25

DLAR-16-40

**DLAR-20-40** 

**DLAR-25-50** 

**DLAR-35-50** 



## **PRODUCT FEATURES**

#### **High Performance Linear/Rotary Motion Adjustable Parameters**

#### **Hollow Rod Soft Landing** Power-off Protection

#### **Precision Resolution Long Life over** 100 Million Cycles

Provide accurate linear and rotary actions of the Z-axis during high-speed motion, with adjustable velocity, thrust, and position parameters, enabling complex actions requiring high frequency and high precision.

The product is compact, light, and thin. It employs a hollow rod design to support pick-and-place tasks. The intelligent soft landing function protects the picked and placed workpiece with precise force control. The Z-axis has a built-in spring to prevent the axis from falling off due to power-off during vertical opera-


Regarding this product, the stroke resolution is up to 0.5 µm, the rotary position resolution is 0.005°. With high-quality guide rail-level related components, it has a service life of up to 100 million cycles, and it is stable and durable.


## **INSTALLATION METHOD**

Install it using the screw holes on the back of the product.

#### **Installation Directions:**


- Horizontal direction
- Vertical installation with the vertical rod pointing down
- Vertical installation with the vertical rod pointing up





## **APPLICATION SCENARIOS**


The force repeatability of  $\pm 10$  g and the micron-level resolution can be applied to the fast pick-and-place, assembly, testing, and other scenarios in semiconductors, 3C electronics, and other industries. The unique linear and rotary motions of the Z-axis of the VLAR series can adapt to more abundant industrial scenarios, such as positioning, correction, and assembly in medical automation, 3C, and packaging automation.



# DLAR-16-25

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult DH-Robotics engineers;
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- 4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust

Continuous thrust\*® 6 N

Calculation formula for linear shaft motor output (vertically down)\*② F=5.68-0.089\*L (For the actual output, refer to the thrust-displacement curve)

Total stroke

 $50 \,\mathrm{g} \sim 200 \,\mathrm{g} \colon \pm 10 \,\mathrm{g}$ Force control accuracy\*  $200 \text{ g} \sim 400 \text{ g}: \pm 5\%$ 

Force constant 0.056 N.M Maximum torque 0.014 N.M Rated torque

Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder)

Rotary positioning repeatability  $\pm 0.02^{\circ}$  (Optical encoder)  $\pm 0.1^{\circ}$  (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass Movable part mass

180 mm x 90 mm x 16.8 mm

Recommended air pressure range\*® -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

24 V DC ±10% Operating voltage

(Linear) 1.2 A (Rotary) 0.6 A Continuous current (Linear) 2.5 A (Rotary) 2.5 A Peak current

Recommended load  $< 100 \, \mathrm{g}$ 

Recommended load inertia 10 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating


Recommended operating 0~40°C, 85% RH or less


environment

International standard compliance CE, FCC, RoHS










# DLAR-16-40

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- \*① Motor output without protective spring; \*② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual
- ondition. For the output calculation of other installation methods, please consult
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support

#### **Performance Specifications** Peak thrust

Continuous thrust\*® Calculation formula for linear shaft motor output (vertically down)\*② F=6.31-0.089\*L (For the actual output, refer to the thrust-displacement curve) Total stroke

 $50 \,\mathrm{g} \sim 200 \,\mathrm{g} \colon \pm 10 \,\mathrm{g}$ Force control accuracy\*®  $200 \text{ g} \sim 400 \text{ g}: \pm 5\%$ 

Force constant 6 N/A Maximum torque 0.056 N.M 0.014 N.M Rated torque

Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Linear positioning repeatability  $\pm 0.02^{\circ}$  (Optical encoder)  $\pm 0.1^{\circ}$  (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass Movable part mass

195 mm x 90 mm x16.8 mm Recommended air pressure range\*® -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Operating voltage 24 V DC ±10%

(Linear) 1 A (Rotary) 0.6 A Continuous current Peak current (Linear) 2.5 A (Rotary) 2.5 A

Recommended load  $< 100 \, \mathrm{g}$ 

Recommended load inertia 10 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating

Recommended operating 0~40°C. 85% RH or less

environment International standard compliance

CE, FCC, RoHS







# DLAR-20-40

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**



# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust

Continuous thrust\*® Calculation formula for linear shaft motor output (vertically down)\*② F=10.53-0.10\*L (For the actual output, refer to the thrust-displacement curve) Total stroke

 $50 g \sim 200 g: \pm 10 g$ 

Force control accuracy\*® 200 g ~ 800 g: ±5%

Force constant 8.7 N/A 0.056 N.M Maximum torque 0.014 N.M Rated torque

Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder) Rotary positioning repeatability  $\pm 0.02^{\circ}$  (Optical encoder)  $\pm 0.1^{\circ}$  (Magnetic encoder)

#### **Mechanical Specifications**

Overall mass 1100 g Movable part mass 195 mm x 106 mm x 20 mm

Recommended air pressure range\*

● -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Operating voltage 24 V DC ±10% (Linear) 1.2 A (Rotary) 0.6 A Continuous current (Linear) 3.5 A (Rotary) 2.5 A Peak current


< 100 g Recommended load Recommended load inertia 10 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C, 85% RH or less


International standard compliance CE. FCC. RoHS




# DLAR-25-50

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- $^*$ ② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult DH-Robotics engineers;
- accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;
- 4 If the air pressure is beyond the specified range, you can consult DH-Robotics engineers

#### **Performance Specifications** Peak thrust

Continuous thrust\*® 8 N

Calculation formula for linear shaft motor output (vertically down)\*② F=8.80-0.056\*L(For the actual output, refer to the thrust-displacement curve) Total stroke

 $50 \,\mathrm{g} \sim 200 \,\mathrm{g}$ :  $\pm 10 \,\mathrm{g}$ Force control accuracy\*®

200 g ~ 600 g: ±5% Force constant 6.6 N/A

Maximum torque 0.056 N.M 0.02 N.M Rated torque

Maximum speed 2000 RPM

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 0.005° (Optical encoder) 0.02° (Magnetic encoder)

Rotary positioning repeatability  $\pm 0.02^{\circ}$  (Optical encoder)  $\pm 0.1^{\circ}$  (Magnetic encoder)

-0.1 Mpa ~ +0.2 Mpa

#### **Mechanical Specifications**

Overall mass Movable part mass

200 mm x 115 mm x 25 mm

#### **Operating Environment**

Recommended air pressure range\* 

•

24 V DC ±10% Operating voltage

(Linear) 1.2 A (Rotary) 1.0 A Continuous current (Linear) 4 A (Rotary) 2.8 A Peak current

Recommended load < 150 g


Recommended load inertia 20 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating IP 40

Recommended operating 0~40°C. 85% RH or less environment


International standard compliance CE, FCC, RoHS



# DLAR-35-50

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- \*① Motor output without protective spring; \*② There is an error of  $\pm$  0.3 N between the theoretical calculation formula and the actual
- ondition. For the output calculation of other installation methods, please cons
- \*3) It is the reference value under the recommended load. The actual force control accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support:

#### **Performance Specifications**

Peak thrust Continuous thrust\*® 18 N

Calculation formula for linear shaft motor output (vertically down)\*② F=17.71-0.09\*L (For the actual output, refer to the thrust-displacement curve)

Total stroke

 $80 \text{ g} \sim 200 \text{ g}: \pm 10 \text{ g}$ Force control accuracy\*® 200 g ~ 1200 g: ±5%

15 N/A Force constant Maximum torque 0.19 N.M Rated torque 0.095 N.M 5000 RPM

Maximum speed Linear encoder resolution 0.5 μm (Optical encoder) 1 μm(Magnetic encoder)

Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder) Rotary encoder resolution 17 BIT (Absolute value of a single coil)

Rotary positioning repeatability ±0.01°

#### **Mechanical Specifications**

2415 g Overall mass 500 g Movable part mass

240 mm x 140 mm x 35 mm

Recommended air pressure range<sup>★®</sup> -0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

48 V DC ±10 % Operating voltage

(Linear) 1.2 A (Rotary) 0.6 A Continuous current

(Linear) 3.5 A (Rotary) 2.5 A Peak current Recommended load < 300 g

Recommended load inertia 120 g.cm<sup>2</sup>


Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating


Recommended operating 0~40°C, 85% RH or less

environment International standard compliance

CE, FCC, RoHS







# **DLSR SERIES Direct Drive Linear Rotary Actuator**

DLSR-25-50



# **PRODUCT FEATURES**

#### **High Performance Linear/Rotary Motion Adjustable Parameters**

#### **Hollow Rod Soft Landing Power-off Protection**

#### **Precision Resolution Long Life over** 100 Million Cycles


Provide accurate linear and rotary actions of the Z-axis during high-speed motion, with adjustable velocity, thrust, and position parameters, enabling complex actions requiring high frequency and high precision. The product is compact, light, and thin. It employs a hollow rod design to support pick-and-place tasks. The intelligent soft landing function protects the picked and placed workpiece with precise force control. The Z-axis has a built-in spring to prevent the axis from falling off due to power-off during vertical operaRegarding this product, the stroke resolution is up to 0.5 μm, the rotary position resolution is 0.005°. With high-quality guide rail-level related components, it has a service life of up to 100 million cycles, and it is stable and durable.

## **INSTALLATION METHOD**


Install it using the screw holes on the back of the product.

#### **Installation directions:**

- Horizontal direction
- Vertical installation with the vertical rod pointing down
- Vertical installation with the vertical rod pointing up







# **APPLICATION SCENARIOS**


DLSR features linear and rotary motion plus  $\pm$  5 N force repeatability, and can be applied in assembly and bonding of 3C products, automatic transplanting, handling,




# DLSR-25-50

**DIRECT DRIVE LINEAR ROTARY ACTUATOR** 

## **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











- \*② There is an error of ± 0.3 N between the theoretical calculation formula and the actual condition. For the output calculation of other installation methods, please consult
- ③ It is the reference value under the recommended load. The actual force control accuracy is related to the load size, running tempo, etc. If you need a higher accuracy, please consult the DH-Robotics technical support;

#### **Performance Specifications**

Peak thrust

Continuous thrust*®	8 N
Calculation formula for linear shaft motor output (vertically down)*②	F=8.80-0.056*L (For the actual output, refer to the thrust-displacement curve)
Total stroke	50 mm

26 N

 $50 \,\mathrm{g} \sim 200 \,\mathrm{g} \colon \pm 10 \,\mathrm{g}$ Force control accuracy\*  $200 \text{ g} \sim 600 \text{ g}: \pm 5\%$ 

6.6 N/A Force constant Holding torque 0.03 N.M 800 RPM Maximum speed

Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder)

Rotary encoder resolution 2000 lines

Rotary positioning repeatability ±0.1°

#### **Mechanical Specifications**

Overall mass	1170 g
Movable part mass	245 g
Size	200 mm x 115 mm x 25 mm
Recommended air pressure range <sup>★</sup>	-0.1 Mpa ~ +0.2 Mpa

#### **Operating Environment**

Operating voltage	24 V DC ±10%	)
Continuous current	(Linear) 1.2 A	(Rotary) 0.8 A
Peak current	(Linear) 3.5 A	
Peak current		. ,


Recommended load  $< 100 \, \mathrm{g}$ Recommended load inertia 20 g.cm<sup>2</sup>

Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval

IP rating

Recommended operating 0~40°C,85% RH以下

International standard compliance CE, FCC, RoHS



# **DLE SERIES Direct Drive Linear** Module

DLE-79-30 DLE-79-50



# **PRODUCT FEATURES**


High Speed High Accuracy	High Energy Density High Stability and Reliability	Compact Design parameters adjustable
The direct drive technology guaranees higher speed and accuracy, that s, the maximum speed of $1.6  \text{m/s}$ , the naximum acceleration of $4  \text{g}$ , and positioning repeatability of $\pm 2  \mu \text{m}$ , oo meet motion control needs in high-end manufacturing industries nocluding precision assembly and	Small size, light weight, large thrust, high speed, stable and reliable, and industry-leading performance.	Featuring compact structure and lighter weight, the product can be easily deployed in a confined space. Bus or pulse control allows for adjustment of force, position and stroke parameters and ease of installation.


# **INSTALLATION METHOD**


Install it using the screw holes on the back of the product.

#### **Installation Directions:**

- Horizontal direction
- Vertical installation with the vertical rod pointing down
- Vertical installation with the vertical rod pointing up








# **APPLICATION SCENARIOS**


DLE features compact design and high energy density. The uniquely designed direct drive structure can be used in precision assembly of 3C products, force controlled pressing, and automatic



# DLE-79-30

**DIRECT DRIVE LINEAR MODULE** 

# **SELECTION METHOD**




# **TECHNICAL SPECIFICATIONS**











\*① Motor output without protective spring;

\*② This formula is used to calculate the output when a mechanical spring is configured. There is an error of  $\pm$  0.5 N between the theoretical calculation formula and the actual condition. For other installation methods, please consult DH-Robotics engineers.

\*③ It is the reference value under the recommended load. The actual force control accuracy is related to the load size, running tempo, etc.lf you need a higher accuracy, please consult the DH-Robotics technical support;

\*④ If the air pressure is beyond the specified range, you can consult DH-Robotics engineers.

<b>Performance Specif</b>	ications
Peak thrust	54 N
Continuous thrust*®	18 N
Calculation formula for linear shaft motor output (vertically down)*②	F=15.21-0.16*L (For the actual output, refer to the thrust-displacement curve)
Total stroke	30 mm
Force control accuracy*®	2 N~15 N:±0.5 N
Force constant	10.6 N/A
Linear encoder resolution	$0.5\mu m$ (Optical encoder) $1\mu m$ (Magnetic encoder)
Linear positioning repeatability	±2 μm (Optical encoder) ±5 μm(Magnetic encoder)
Mechanical Specific	ations

690 g

	Overall mass	690 g			
	Movable part mass	340 g			
	Size	130.5 mm x 79 mm x 26 mm			
	Recommended air pressure range*®	Without vacuum			
	Operating Environment				
Ī	Operating voltage	48 V DC +10%			

(Linear) 5.1 A Peak current < 1000 g (for horizontal applications) Recommended load < 500 g (for vertical applications)

(Linear) 1.7 A


Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating

Continuous current

Recommended operating 0~40°C, 85% RH以下

International standard compliance CE, FCC, RoHS






<sup>\*</sup>Note: For customization fees, consult the company's sales staff

# DLE-79-50


**DIRECT DRIVE LINEAR MODULEZ** 

## **SELECTION METHOD**



<sup>\*</sup>Note: For customization fees, consult the company's sales staff


# **TECHNICAL SPECIFICATIONS**











**Performance Specifications** 54 N Peak thrust Continuous thrust\*® Calculation formula for linear shaft motor output (vertically down)\*② F=16.49-0.16\*L (For the actual output, refer to Total stroke 50 mm Force control accuracy\*® 2 N~15 N: ±0.5 N Force constant 10.6 N/A Linear encoder resolution 0.5 µm (Optical encoder) 1 µm (Magnetic encoder) Linear positioning repeatability ±2 μm (Optical encoder) ±5 μm (Magnetic encoder)

Mechanical	Specifications
Overall mass	970 g

180.5 mm x 79 mm x 26 mm

Recommended air pressure range\* Without vacuum

#### **Operating Environment**

Movable part mass

Operating voltage	48 V DC ±10%
Continuous current	(Linear) 1.7 A
Peak current	(Linear) 5.1 A
	< 000 = (far barinantal anni


(900 g (for horizontal applications) Recommended load < 400 g (for vertical applications) Refer to Maintenance Instructions for DH-Robotics Linear coil actuator Maintenance interval


IP rating

Recommended operating 0~40°C, 85% RH or less

International standard CE, FCC, RoHS compliance

) If the air pressure is beyond the specified range, you can consult DH-Robotics engineers





<sup>\*</sup>① Motor output without protective spring;
\*② This formula is used to calculate the output when a mechanical spring is configured. There is an error of  $\pm$  0.5 N between the theoretical calculation formula and the actual theoretical configuration of the config condition. For other installation methods, please consult DH-Robotics engineers. accuracy is related to the load size, running tempo, etc.If you need a higher accuracy please consult the DH-Robotics technical support;

# **LINEAR COIL ACTUATOR DRIVE**

The following table provides driver model options:

Drive	Communication method	Operating mode	I/O	Note	Model
SAC-N2	USB	Velocity mode Torque mode Position mode	5 DI on each axis	Integrated dual-axis control Compact	
(DH-ROBOTICS)	EtherCAT	Position track mode Velocity track mode Torque track mode Cyclic Synchronous Position mode Cyclic Synchronous Velocity mode Cyclic Synchronous Torque mode	2 DO on each axis  1 Al on each axis  1 single-ended pulse input  1 single-ended	design Excellent force control accuracy Force control Force control Built-in soft landing	EtherCAT: SAC-N2-EC- U-03-A1-03- A1
120 to 100	Pulse control	Pulse + direction mode CW/CC2 mode Ortho mode	direction input	Built-in electronic gear ratio	
ISD (DH-ROBOTICS)	USB	Velocity mode Torque mode Position mode		Small size with excellent force control accuracy. The	
(c	EtherCAT (CoE) (changeable to CANopen)	Position track mode Velocity track mode Torque track mode Interpolated position mode Cyclic Synchronous Position mode Cyclic Synchronous Velocity mode Cyclic Synchronous Torque mode	6 digital inputs 4 digital outputs 2 12-bit analog inputs	built-in soft landing function can be configured with rich parameters and is flexible for use.	EtherCAT: ISD-N-EC-U- 10A1
	USB	Velocity mode Torque mode			
SERVO TRONIX	RS232	Position mode		Medium	
	Analog voltage	Analog velocity mode Analog torque mode	8 digital inputs 3 fast digital inputs 6 digital outputs 2 fast digital outputs	size, good force control accuracy, no soft landing	EtherCAT:
	EtherCAT (CoE) (changeable to CANopen)	Position track mode Velocity track mode Torque track mode Interpolated position mode Cyclic Synchronous Position mode Cyclic Synchronous Velocity mode Cyclic Synchronous Torque mode	1 16-bit analog input 2 14-bit analog inputs 1 analog output	function, and configu- rable I/O trigger script	DEC2

Drive	Communication method	Operating mode	I/O	Note	Model
	USB				
	RS232	Velocity mode Torque mode Position mode		Small size, excellent force control	
ELMO	EtherNET UDP				
	EtherCAT (CoE) (changeable to CANopen)	Position track mode Velocity track mode Torque track mode Interpolated position mode Cyclic Synchronous Position mode Cyclic Synchronous Velocity mode Cyclic Synchronous Torque mode	6 digital inputs 2 digital outputs 1 analog input	accuracy, built-in soft landing function, and programma ble inside the drive	EtherCAT: G-MOL- WHI5/100EE

www.dh-robotics.com 55/56

### **Customer trust**

More than 800 customers around the world are using DH-Robotics products The number of customers continues to grow rapidly. . .



















































# **Product Distribution**

#### **Chinese Agent Distribution Cties**

Beijing/Changchun/Changsha/Chengdu/Chongqing/Dalian/Dongguan/Guangzhou/Hangzhou/Hefei/Jinan/Nanchang/Nanjing/Ningbo/Qingdao/Shanghai/Shenyang/Shenzhen/Suzhou/Wuhan/Wuxi/Xi'an/Xiamen/Yantai/Yangzhou/Zhengzhou/Zhuhai

## **Overseas Agents Distribution Area**

**Europe:** Spain / France / Italy / Germany / UK / Czech Republic / Romania / Russia /

Netherlands / Lithuania / Sweden / Denmark / Norway

Asia: Israel / Bangladesh / India / Japan / Thailand / South Korea / Malaysia

**Australia:** Australia / New Zealand **America:** United States / Mexico

Middle East: Saudi Arabia / Tunisia / Türkiye

# DH-ROBOTICS A professional provider of precision motion control products and solutions

www.dh-robotics.com 57/58